



M2SFPT

2 Port 1Gbps Test Module

Product Order Numbers

XenaCompact	C1-M2SFPT
XenaBay	M2SFPT

Advanced timing test module for Synchronous Ethernet test apps

The M2SFPT is a low-cost 2-port 1 Gigabit Ethernet test module for Layers 2-3. Based on Xena's advanced architecture, the M2SFPT is an advanced timing test module developed for Synchronous Ethernet test applications. It is available for both the 4U 12-slot XenaBay chassis and the robust, transportable 1U XenaCompact chassis.

The M2SFPT comes complete with Xena's free XenaManager software - an easy-to-use GUI for handling both routine and advanced test schedules that includes XenaScripting, XenaIntegrator, Xena2544, Xena1564, Xena3918 and Xena2889.

TOP FEATURES - M2SFPT

- Price/performance
- Ideal for SynchE testing
- Ease of use
- Free software (incl. XenaManager GUI, XenaScripting, XenaIntegrator, Xena2544, Xena1564, Xena3918 and Xena2889)
- Free 12-month hardware warranty
- 36 months free software updates
- Free tech support product lifetime



PORT LEVEL FEATURES

Interface category	10/100/1000M Ethernet
Number of test ports	2 x 10/100/1000M
Interface options	10/100/1000BASE-T ¹⁾ or 1000BASE-X (SFP-MSA) or 100BASE-FX ²⁾ or 100BASE-BX ²⁾ or SFP-ToC ³⁾
Number of transceiver module cages	2 x SFP
Port statistics ⁴⁾	Link state, FCS errors, pause frames, ARP/PING, error injections, training packet All traffic: RX and TX Mbit/s, packets/s, packets, bytes Traffic w/o test payload: RX and TX Mbit/s, packets/s, packets, bytes
Adjustable Inter Frame Gap (IFG)	Configurable from 16 to 56 bytes, default is 20B (12B IFG + 8B preamble)
Transmit line rate adjustment	Ability to adjust effective line rate by forcing idle gaps equivalent to -1000 ppm (increments of 10 ppm)
Transmit line clock adjustment	From -400 to 400 ppm in steps of 0.001 ppm (shared across all ports)
ARP/PING	Supported (configurable IP and MAC address per port)
Field upgradeable	System is fully field upgradeable to product releases (FPGA images and Software)
Histogram statistics ⁴⁾	Two real-time histograms per port. Each histogram can measure one of RX/TX packet length, IFG, jitter, or latency distribution for all traffic, a specific stream, or a filter
Tx disable	Enable/disable of optical laser or copper link
IGMPv2 multicast join/leave)	IGMPv2 continuous multicast join, with configurable repeat interval
Oscillator characteristics	<ul style="list-style-type: none"> • Initial Accuracy is 3 ppm • Frequency drift over 1st year: +/- 3 ppm (over 15 years: +/- 15 ppm) • Temperature Stability: +/- 20 ppm (Total Stability is +/- 35 ppm)

ADVANCED TIMING FEATURES**

Selectable Tx line rate	Tx line rate can be referenced to either local clock oscillator (adjustable in steps of 1 ppm), SMA input, or from the Rx line rate for Synchronous Ethernet applications. The Tx line rate complies with SONET/SDH/SynchE with respect to wander and jitter.
Jitter attenuation	Selectable loop bandwidth for jitter attenuation: 114 Hz, 229 Hz, 460 Hz, 1864 Hz, or 7834 Hz loop bandwidth
SMA input	<ul style="list-style-type: none"> • 10.0 MHz, or 2.048 MHz Tx line rate reference clock SMA input (Drift/wander is passed from SMA input to Tx line rate) • 250mV-2.5V, loaded 50 ohm, square wave format
SMA output	<ul style="list-style-type: none"> • Selectable as either Tx Line Rate Reference (10 MHz, 2.048 MHz, or 156.25 MHz), a trigger output indicating Ethernet start of frame, slave mode pass-through (SMA output = SMA input), or as the Recovered Rx clock(s) • 700mV, loaded 50 ohm, square wave format



TRANSMIT ENGINE

Number of transmit streams per port	32 (wire-speed) continuous
	Each stream can generate millions of traffic flows through the use of field modifiers
Test payload insertion per stream	Wire-speed packet generation with timestamps, sequence numbers, and data integrity signature optionally inserted into each packet.
Stream statistics ⁴⁾	TX Mbit/s, packets/s, packets, bytes, FCS error, Pause
Bandwidth profiles	Burst size and density can be specified. Uniform and bursty bandwidth profile streams can be interleaved
Field modifiers	16-bit header field modifiers with inc, dec, or random mode. Each modifier has configurable bit-mask, repetition, min, max, and step parameters. 2 modifiers per stream.
Packet length controls	Fixed, random, butterfly, and incrementing packet length distributions. Packet length from 56 to 16384 bytes
Packet payloads	Repeated user specified 1 to 18B pattern, a 8-bit incrementing pattern
Error generation	Undersize length (56B min) and oversize length (16384 max.) packet lengths, injection of sequence, misorder, payload integrity, and FCS errors
TX packet header support and RX autodecodes	Ethernet, Ethernet II, VLAN, ARP, IPv4, IPv6, UDP, TCP, LLC, SNAP, GTP, ICMP, RTP, RTCP, STP, MPLS, PBB, or fully specified by user
Packet scheduling modes	<ul style="list-style-type: none"> • Normal (stream interleaved mode). Standard scheduling mode, precise rates, minor variation in packet inter-frame gap. • Strict Uniform. New scheduling mode, with 100% uniform packet inter-frame gap, minor deviation from configured rates • Sequential packet scheduling (sequential stream scheduling). Streams are scheduled continuously in sequential order, with configurable number of packets per stream

RECEIVE ENGINE

Number of traceable Rx streams per port	648 (wire-speed)
Automatic detection of test payload for received packets	Real-time reporting of statistics and latency, loss, payload integrity, sequence error, and misorder error checking
Jitter measurement	Jitter (Packet Delay Variation) measurements compliant to MEF10 standard with 8 ns accuracy
Stream statistics ⁴⁾	<ul style="list-style-type: none"> • RX Mbit/s, packets/s, packets, bytes. • Loss, payload integrity errors, sequence errors, misorder errors • Min latency, max latency, average latency • Min jitter, max jitter, average jitter
Latency measurements accuracy	±16/32 ns (opto/elec)
Latency measurement resolution	8 ns (Latency measurements can calibrate and remove latency from transceiver modules)
Number of filters:	6 x 64-bit user-definable match-term patterns with mask, and offset 6 x frame length comparator terms (longer, shorter) 6 x user-defined filters expressed from AND/OR'ing of the match and length terms.
Filter statistics ⁴⁾	Per filter: RX Mbit/s, packets/s, packets, bytes.

CAPTURE

Capture criteria	All traffic, stream, FCS errors, filter match, or traffic without test payloads
Capture start/stop triggers	Capture start and stop trigger: none, FCS error, filter match
Capture limit per packet	16 – 16384 bytes
Wire-speed capture buffer per port	16 kB
Low speed capture buffer per port (10Mbit/sec)	4096 packets (any size)

- 1) Requires Finisar SFP transceiver FCLF-8521-3 with sgmi host interface
2) Requires Source Photonics SFP transceivers with sgmi host interface

- 3) requires that the other end operates as Auto Negotiation master
4) counter size: 64 bits

PHYSICAL

1U XenaCompact

- W: 19" (48.26 cm)
- H: 1.75" (4.45 cm)
- D: 9.8" (25 cm)
- Weight: 10 lbs (4.5 kg)

4U XenaBay

- W: 19" (48.26 cm)
- H: 7" (17.78 cm)
- D: 19.7" (50 cm)
- Weight: 36.4 lbs (16.5 kg)

ENVIRONMENTAL

- Operating Temperature: 10 to 35° C
- Storage Temperature: -40 to 70° C
- Humidity: 8% to 90% non-condensing

POWER

- AC Voltage: 100-240V
- Frequency: 50-60Hz
- Max. Power: 90 Watts (XenaCompact) / 120W (XenaBay)
- Max. Current: 0.8A with 120V supply, and 0.4A with 240V supply

REGULATORY

FCC (US), CE (Europe)



Xena Networks is an award-winning manufacturer of advanced Gigabit Ethernet test and measurement solutions.



Presented by:

Mimetrix Technologies
11160 C-1 South Lakes Drive
Suite 190
Reston, VA 20191
Phone: 571-306-1234
Email: xena@mimetrix.com

